

# TX-5011-03-1

## Shock sensor 868 MHz Gen2, white

The shock sensor is designed to detect the vibrations made by an intruder trying to break a window or door. The sensor has an internal reed allowing to supervise a door or window using the door magnet that is included.

Sensitivity and pulse count options can be set using DIP switches. A jumper allows to select which reed is in use (left or right or none). In walk-test mode, the blue LED on the front cover will light up when the sensor is in alarm state.



#### **Details**

- Learn-Mode technology
- Supervised transmissions
- LED indicating sensor status
- Detects opening of door or window
- Magnet included
- Gross attack and pulse count detection modes
- Compatible with Interlogix 868 MHz Gen2 receivers

## TX-5011-03-1Shock sensor 868 MHz Gen2, white

### **Technical specifications**

General	
Product type	Magnetic contact, Shock with analyser
Wired / wireless	
Wired / wireless	Wireless
Wireless frequency	868 MHz AM
Electrical	
Current consumption	10 μA (typical standby)
Batteries	1 x 3 V Lithium
Battery lifetime	3 to 5 years
Physical	
Physical dimensions	114 x 32 x 32 mm
Colour	White



As a company of innovation, Carrier Fire & Security reserves the right to change product specifications without notice. For the latest product specifications, visit firesecurityproducts.com online or contact your sales representative.